



Description

This product allows connection, from one signal input auxiliary level, up to 20 signal sockets, each one totally independent from others. The use of this product is recommended in specific application, you need to broadcast audio signal from sound system towards other equipment such as recording for media, radio, TV, etc.

CONNECTION AND ADJUSTMENT INSTRUCTION

- 1.- Connect audio signal from sound system to signal input (DIN).
- 2.- Activation of mains switch "ON".
- 3.- Adjust potentiometer of volume from the back, in order that with modulation at adjusted level, the green led lights "MOD" intermittently.

Signal outputs (1 - 10)

- Signal:	Balanced.
- Level:	0 dBm.
- Impedance:	600Ω.
- Connector:	XLR.

Signal outputs (11 - 20)

- Signal:	Unbalanced.
- Level:	-10 dBm.
- Impedance:	600Ω.
- Connector:	Jack 6 mm.
- Sensitivity:	100 mV.
- Power supply:	230 VAC
- Weight:	6.5 Kg.
- Dimensions:	428x330x100.

